



WIRE MESH SYSTEM INSTALL

WIRE MESH SYSTEM FOR BUCKLEY FENCE INSTALLATION INSTRUCTIONS

Our Wire Mesh Clips allow an easy way to add any wire mesh to your Buckley Fence, vinyl, pipe, or any hollow tube fence. We recommend vinyl-dipped wire mesh for abrasion protection on the fence coating and the most striking look.

REQUIRED MATERIALS

1. No. 2 Phillips Driver
2. Step drill
3. Chain link wire mesh; galvanized and black vinyl coated recommended, but any wire mesh will work with this system.

1 DRILLING THE HOLES

1. Drill holes in the posts and rails in accordance with the Wire Mesh diagrams on [page 27](#).
2. Position mesh over the fence in the desired position.

2 INSTALLING THE WIRE MESH CLIPS

1. Insert a Wire Mesh Clip into one of the holes you've just drilled.
2. Mount the wire mesh through the wire mesh clips. Ensure that the mesh is placed in a way that it is controlled vertically and horizontally. Do this by positioning the two teeth that are on the clamshell wash clamp across both a vertical and horizontal wire.
3. Insert the No. 2 Phillips-driver into the drill. Drill Wire Mesh Clip onto the fence. As you drill, the rubber well nut will seal the hole, ensuring no damage to the fence finish.
4. Repeat steps 3-5 for the remaining Wire Mesh Clips.

